

# EnerGenie Programmable surge protector

EG-PMS2

## YOUR SWITCH IS MY COMMAND

- EG-PMS2 is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



Input voltage 220 – 230 VAC~ 50 – 60 Hz

Maximum load current 10A

Maximum current consumed by the EG-PMS2 from the computer USB port: 350mA

Maximum quantity of EG-PMS2 connected to one computer at the same time: no restrictions (only restricted by the maximum allowed quantity of the USB devices)

Plug and Play Hardware schedule restrictions:

Maximum number of independent hardware schedules: 16 pcs Time interval between the events: from 1 minute to 180 days

Timer accuracy: not more than 3 seconds error per day Working temperature range: from +10 to +40 degrees Celsius

Dimensions: 378 x 98 x 55 mm Net weight: not more than 1.3 kg

#### Vlastnosti

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Timers stays active even when the managing PC is turned off
- Child protected sockets
- Mounting holes

### Packaging

Množství v kartonu, kusy Velikost kartonu, CUM Váha kartonu, kg Individual package size LxWxH: Carton size LxWxH: Země původu Čárkový kód (EAN) Customs code

#### Obsah balení

#### EG-PMS2

User manual USB cable CD with Power Manager software for Windows

#### Certifikát



Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com

10 0.04413625 12.8 465x145x65 mm 425x335x310 mm CN 8716309074155 8544429090

## Systémové požadavky

Computer running Windows 7/8/10/11 is required for using the Power Manager software A free USB port