

EnerGenie Programmable surge protector with LAN interface

EG-PMS2-LAN

YOUR SWITCH IS MY COMMAND

- EG-PMS2-LAN is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your local network or Internet, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PMS2-LAN via Internet from all over the world, even with your smartphone.
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via LAN or Internet
- Switch electric devices on or off with your smartphone, wherever you are
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals
- Perfect solution for security systems , sauna , aquariums, pet habitats, etc.



Īpašības

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Because of the LAN interface and the built-in web-server, EG-PMS2-LAN can be accessed from any computer within your local network (via an Internet browser or Power manager software)

Packaging

Skaitis iepakojumā, gab.	10
Iepakojuma izmērs, kub.m	0.04557
Iepakojuma svars, kg	12.16
Individual package size LxWxH:	400x145x60 mm
Carton size LxWxH:	420x350x310 mm
Izcelsmes valsts	CN
Svītrkods	8716309074162
Customs code	8544429090

Iepakojuma saturs

EG-PMS2-LAN
User manual and Quick installation guide
RJ45 cross-over cable (red), RJ45 LAN cable (grey)
CD with Power Manager software for Windows

Sertifikāti



Specifikācija

Input voltage: up to 250 VAC, 50 – 60 Hz
Maximum load current: 10A
Maximum power consumption: 2.5 W
Built-in power supply
Power cord: 1.8 m
Surge protection: Type3, Up=1.2KV for L-N, Uoc=4KV for L-N Uo=230V
Uc=250V Ucs=1.1X230V=253V
Hardware schedule possibilities:
Maximum number of independent hardware schedule events – 45 per socket

Time setting accuracy in seconds
Combine periodical and once events
Timer accuracy: not more than 2 seconds error per day in case that power is always present. Otherwise there can be an additional up to 2 seconds error per each "power off"
Indoor use only
Dimensions: 378 x 98 x 55 mm
Net weight: up to 1 kg

Sistēmas prasības

Local area network with RJ45 sockets
Any Internet-enabled computer connected to the local area network
Computer running Windows 7/8/10/11 is required for using the Power Manager software (use of this software is not compulsory)