

|   |  |  |   |
|---|--|--|---|
|  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with<br/>USB and LCD display</b></p>  |  |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with<br/>USB and LCD display</b></p>   |   |
|  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <ul style="list-style-type: none"> <li>• Informative LCD display</li> <li>• Provides backup power - prevents data loss</li> <li>• Protects your sensitive and valuable equipment</li> <li>• Compact and reliable - ideal for home and small office use</li> </ul>  <p><b>UPS<br/>with USB<br/>and LCD display</b></p> <p>1500 VA</p> |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with USB and LCD display</b></p> <p><b>Specifications:</b></p> <ul style="list-style-type: none"> <li>Type: line interactive</li> <li>Waveform: sine wave (AC mains), modified (square) sine wave (battery)</li> <li>Input: 220 V AC ± 25 %, 50 Hz / 60 Hz ± 10 %</li> <li>Output: 220 V AC ± 10 %, 50 Hz / 60 Hz ± 1 % (220 V AC ± 5 % at inverter mode)</li> <li>Switching time: less than 10 ms</li> <li>Backup time: 8...20 mins (depends on the load)</li> <li>Battery: sealed lead-acid 12 V DC / 8 Ah x 2 pcs</li> <li>Charge time: up to 12 hours</li> <li>Sockets: 1 x C14 input, 3 pcs x C13 output, 2 pcs x german Shuko</li> <li>USB control interface: BF socket</li> <li>Operating conditions: 0 °C – 40 °C, at humidity 20 % – 90 % RH non condensing</li> <li>Power: 1500 VA (900 W)</li> <li>Charging current: up to 1.2 A</li> <li>Noise: &lt; 45 dB at 1 m distance</li> <li>Dimensions: 400 mm x 125 mm x 220 mm</li> <li>Net weight: 10.8 kg</li> </ul> <p><b>System requirements:</b></p> <ul style="list-style-type: none"> <li>Software is compatible with Windows® Vista, Windows® 7 and Windows® 2008 server</li> </ul> <p><b>Package contents:</b></p> <ul style="list-style-type: none"> <li>UPS</li> <li>Power cord</li> <li>USB cable</li> <li>Software CD</li> <li>Spare fuse</li> </ul>   <p>EG-UPS-034</p>  <p>8 712 37 113 83 0</p> <p>CE, RoHS, WEEE, Recycle, Made in China</p> <p><small>All brands and signs are registered trademarks of their respective owners.</small></p> |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <ul style="list-style-type: none"> <li>• Informative LCD display</li> <li>• Provides backup power - prevents data loss</li> <li>• Protects your sensitive and valuable equipment</li> <li>• Compact and reliable - ideal for home and small office use</li> </ul>  <p><b>UPS<br/>with USB<br/>and LCD display</b></p> <p>1500 VA</p> |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with USB and LCD display</b></p> <p><b>UPS with USB and LCD display, 1500 VA</b></p> <ul style="list-style-type: none"> <li>Intermittent 1500 VA power supply for PCs</li> <li>Automatic output voltage regulation (AVR)</li> <li>USB interface</li> <li>LCD status indication</li> <li>Short circuit protection</li> <li>Surge, spike and lightning protection</li> <li>Audible and visual alarms</li> <li>Overcharge and overdischarge protection including practical UPS Management software</li> </ul> <p><b>1500 VA UPS mit LCD</b></p> <ul style="list-style-type: none"> <li>Automatische Ausgangsspannungsregulierung (AVR)</li> <li>USB-Schnittstelle</li> <li>LCD-Statusanzeige</li> <li>Kurzschlusssicherung</li> <li>Überspannungs- und Spannungsspitzenbesicherung sowie Blitzschutz</li> <li>Hörbare und sichtbare Alarme</li> <li>Absicherung vor Überladung und Tiefentladung</li> </ul> <p><b>Noodstroomvoeding met LCD, 1500 VA</b></p> <ul style="list-style-type: none"> <li>1500 VA noodstroomvoeding (UPS) voor o.a. PCs</li> <li>Automatische AC spanningregelaar (AVR)</li> <li>Interfacede overspanningsbeveiliging biedt bescherming tegen kortsluiting en spanningstikken veroorzaakt door bijvoorbeeld blikseminslag</li> <li>Hoortbaar en zichtbaar alarm bij stroomuitval</li> <li>LCD status indicator</li> <li>Interne batterij met bescherming tegen overladen of te veel ontladen</li> <li>Inclusief praktische UPS Management software</li> </ul> <p><b>Источник бесперебойного питания 1500 Вольт-ампер с ЖК-дисплеем и USB-интерфейсом</b></p> <ul style="list-style-type: none"> <li>Автоматический регулятор выходного напряжения (AVR)</li> <li>USB-интерфейс для управления и индикации</li> <li>ЖК-индикатор статуса</li> <li>Защита от короткого замыкания</li> <li>Защита от выбросов напряжения, полей и молний</li> <li>Звуковое и визуальное оповещение о событиях</li> <li>Защита батареи от перезарядки и глубокого разряда</li> </ul> <p><b>Джерело безперебійного живлення 1500 Вольт-ампер з РК-дисплеєм та USB-інтерфейсом</b></p> <ul style="list-style-type: none"> <li>Джерело безперебійного живлення</li> <li>1500 Вольт-ампер</li> <li>Автоматичний регулятор вихідної напруги (AVR)</li> <li>USB-інтерфейс для управління і індикації</li> <li>ЖК-індикатор статусу</li> <li>Захист від короткого замикання</li> <li>Захист від викидів напруги, полів і блискавок</li> <li>Звуковий і візуальний оповіщення про події</li> <li>Захист батареї від перезаряду і глибокого розряду</li> </ul> <p><b>Zasilacz awaryjny UPS 1500 VA z LCD</b></p> <ul style="list-style-type: none"> <li>Automatyczna regulacja napięcia wyjściowego (AVR)</li> <li>Interfejs USB</li> <li>Wyświetlacz LCD informujący o pracy urządzenia</li> <li>Zabezpieczenie przeciw zwarzeniom</li> <li>Zabezpieczenie przeciwprzepięciowe</li> <li>Ochrona odgromowa</li> <li>Alarm dźwiękowy i świetlny</li> <li>Ochrona przed przeładunkiem oraz przed całkowitym wyczerpaniem akumulatora</li> </ul> |
| <p>size: 390x180x295 mm</p>  <p>Pantone blue 072C</p>  <p>Pantone 376C</p>  <p>60% black</p>   |  |  |   |

size: 390x180x295 mm



Pantone blue 072C



Pantone 376C



60% black