


www.energenie.com



3000 VA

Pure sine UPS

- Pure sine wave output
- Provide backup power – prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sine wave input





3000 VA

Pure sine UPS

- Pure sine wave output
- Provide backup power – prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sine wave input



energenie

3000 VA pure sine UPS

ULTIMATE DEFENCE

Specifications:
 • Type: line interactive
 • Waveform sine 5% distortion at linear load, PF > 0.8
 • Input: AC 220V ± 25%, 50 Hz / 60 Hz ± 10%
 • Output: AC 220V ± 12%, 50 Hz / 60 Hz ± 1% (AC 220V ± 5% at inverter mode)
 • Switching time up to 10 ms typically
 • Backup time: 10...30 mins (depends on the load)
 • Battery: 51 mm x 65 mm x 94 mm, sealed lead-acid 12V / 9 Ah, F2 terminals x 4 pcs
 • Charge time: up to 24 hours
 • Sockets: C14 input, 4 outputs x C13, USB-BF connector
 • Operating conditions: 0 °C – 40 °C, at humidity 10% – 90% RH non-condensing
 • Power: 3000 VA (2400 W)
 • Charging current: up to 1.7 A
 • Noise: < 50 dB at 1 m distance
 • Dimensions: 407 mm x 336 mm x 190 mm
 • Product weight: 28.1 kg

System requirements:
 • In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

Package contents:
 • UPS
 • Power input cord
 • Power IEC output cord x 2 pcs

EG-UPS-PS3000-01
 0 4716 20 910 05 337 0

CE ENEC ETL Made in China
 All brands and logos are registered trademarks of their respective owners.

energenie

3000 VA pure sine UPS

ULTIMATE DEFENCE

3000 VA UPS
 • Uninterruptible power supply with pure sine wave output
 • USB interface
 • Automatic AC voltage regulation (AVR)
 • Intelligent overload- and short-circuit protection
 • Audible and visual alarms
 • LED display and LED status indication
 • Internal battery with overcharge and over-discharge protection

3000 VA UPS
 • Automatische Ausgangsspannungsgleichung (AVR)
 • Reiner Sinus-Signalform
 • LED-Statusanzeige
 • Kurzschlusssicherung
 • Überspannungs- und Spannungsspitzenüberschuss sowie Blitzschutz
 • Hörsicht und sichtbare Status
 • Abschaltung vor Überladung und Tiefentladung

3000 VA UPS
 • Automatische oostroomvoorziening met zuivere sinusgolf
 • USB aansluiting
 • Automatische AC spanningregelaar en stabilisator (AVR)
 • Intelligentie beveiliging tegen overbelasting en kortsluiting
 • Hoofdschakel met zichtbaar alarm bij stoornissen
 • LED-scherm en LED-statusaanduiding
 • Interne batterij met bescherming tegen overladen of teveel ontladen

Джерело безперебійного живлення 3000 Вольт-ампер
 • Джерело безперебійного живлення з синусоїдальним сигналом на виході
 • USB-інтерфейс
 • Автоматичний регулятор вихідної напруги (AVR) і короткого замикання
 • Інтелектуальний захист від перевантаження і короткого замикання
 • Звуковий і візуальний сповіщення про події
 • Світлодіодний дисплей та світлодіодний індикатор статусу
 • Замість батареї від пере зарядки і глибокого розряду

3000 VA UPS
 • Запобігання спотворення сигналів
 • Порт USB для налаштування
 • Автоматична регуляція напруги AC (AVR)
 • Інтелектуальне захист пере навантаження і короткого замикання
 • Акустичні і візуальні сповіщення про аварійні ситуації
 • Внутрішня батарея з захистом від перезарядки та глибокого розряду

size: 333x145x238 mm



Pantone blue 072C



Pantone 376C