


www.energenie.com



2000 VA
Pure sine UPS

- Pure sine wave output
- Provide backup power – prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sine wave input





2000 VA
Pure sine UPS

- Pure sine wave output
- Provide backup power – prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sine wave input





energenie
2000 VA pure sine UPS

ULTIMATE DEFENCE

Specifications:

- Type: line interactive
- Waveform sine 5% distortion at linear load, PF > 0.8 (on battery)
- Input: AC 220V ± 25%, 50 Hz / 60 Hz ± 10%
- Output: AC 220V ± 12%, 50 Hz / 60 Hz ± 1% (AC 220V ± 5% at inverter mode)
- Switching time up to 10 ms
- Backup time: 10...30 mins (depends on the load)
- Battery: 51 mm x 65 mm x 94 mm, sealed lead-acid 12V / 9 Ah, F2 terminals x 3 pcs
- Charge time: up to 24 hours
- Sockets: C14 input, 4 outputs x C13, USB-BF connector
- Operating conditions: 0 °C – 40 °C, at humidity 10% – 90% RH non-condensing
- Power: 2000 W (1600 W)
- Charging current: up to 3.2 A
- Noise: < 50 dB at 1 m distance
- Dimensions: 412 mm x 215 mm x 144 mm
- Product weight: 18.5 kg

System requirements:

- In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

Package contents:

- UPS
- Power cord
- Spare fuse

EG-UPS-PS2000-01
0 176 209 910 67353

CE ENEC ETL Made in China

All brands and logos are registered trademarks of their respective owners.



energenie
2000 VA pure sine UPS

ULTIMATE DEFENCE

2000 VA UPS

- Uninterruptible power supply with pure sine wave output
- USB interface
- Automatic AC voltage regulation (AVR)
- Intelligent overload and short-circuit protection
- Audible and visual alarms
- LED display and LED status indication
- Internal battery with overcharge and over-discharge protection

2000 VA UPS

- Automatische Ausgangsspannungregulierung (AVR)
- Reiner Sinus-Wellenform
- LED-Statusanzeige
- Karobehausung
- Überspannungs- und Spannungsspitzenüberschuss sowie Blitzschutz
- Hörbare und sichtbare Alarme
- Absicherung vor Überladung und Tiefentladung

2000 VA UPS

- Automatische oordspanningsregulering met zuivere sinusgolf
- USB aansluiting
- Automatische AC spanningregelaar en stabilisator (AVR)
- Intelligente beveiliging tegen overbelasting en kortsluiting
- Hörbare en zichtbare alarm bij overspanning
- LED-scherm en LED-statusaanduiding
- Interne batterij met bescherming tegen overladen of teveel ontladen

Источники бесперебойного питания 2000 Вольт-ампер

- Источники бесперебойного питания с синусоидальным выходным сигналом
- USB интерфейс
- Автоматический регулятор выходного напряжения (AVR)
- Интеллектуальная защита от перегрузки и коротких замыканий
- Звуковые и визуальные оповещения о сбоях
- Светодиодная и ЖК-индикация статуса
- Защита батарей от перезарядки и глубокого разряда

Джерело безперебійного живлення 2000 Вольт-ампер

- Джерело безперебійного живлення з синусоїдальним вихідним сигналом
- USB інтерфейс
- Автоматичний регулятор вихідної напруги (AVR)
- Інтелектуальний захист від перевантажень і коротких замикань
- Звукові і візуальні сповіщення про події
- Світлодіодна та ЖК-індикація статусу
- Захист батарей від перезарядки і глибокого розряду

2000 VA UPS

- Запа изградбна сушта синусоид
- Port USB за контрола
- Автоматиска регулација напруга AC (AVR)
- Интелигентна заштитна преградба прекомерно и краткотрајно
- Акустички и визуелни оповестувања за грешки
- Унутрешна LED и LED индикација за статус
- Внатрешна батерија со заштита од претеропрегрев и дубоко напонско оптованување

size: 333x145x238 mm

Pantone blue 072C

Pantone 376C