

BTCC-002

BT v.2.1 + EDR car kit, class II

STAY CONNECTED

- Make safe handsfree phone calls
- Connect 2 mobile phones at once
- Easy to use one-touch control
- Use for 7.5 hours without charging
- Make safe handsfree phone calls while driving your car, with this compact BT carkit. This carkit is easy to use and combines an excellent sound quality with a contemporary design. No complex installation required. Simply attach the MobileBird to the sun visor in your car, switch on the BT on your mobile phone and the carkit is ready to use. The buttons on the carkit allow you to answer a call, redial the last number or to adjust the volume.

Features

- BT carkit with excellent full-duplex sound quality
- Multi-link technology: connect two devices simultaneously
- One-touch button for answering, rejecting and redial calls
- Up to 7.5 hours talking time and 800 hours of standby time, without charging
- Working distance up to 10 meters

Packaging

Q'ty in crtn, pcs	60
Crtn volume, CUM	0.079007
Crtn weight, kgs	16
Individual package size LxWxH:	112x40x148 mm
Carton size LxWxH:	470x410x410 mm
Country of origin	CN
Barcode	8716309072847
Customs code	8522900090

Package contents

BT Handsfree car kit
Car charger + USB cable
Sun visor clip
User manual

Certificates



Specifications

BT v2.1+ EDR

Operating Frequency Band: 2.4GHz ~ 2.48GHz unlicensed ISM band

RF power class II: working distance is up to 10 m

Integrated echo cancellation and Noise suppressor

Built in speaker and microphone

Battery type: rechargeable lithium-polymer battery 3.7 VDC, 750 mAH

Charging time: up to 3 hours

Talk time: up to 7.5 hours

Standby time: more than 800 hours

Car charger: input DC 12-24 VDC; output 5.0 ± 0.2 VDC up to 1 A; black color

Dimensions: 118 x 47 x 15 mm

System requirements

BT enabled mobile phone