

12 V Car power inverter, 300 W

EG-PWC-042

PURE POWER

- A 230V power source in your car
- Practical USB port for charging mobile devices



Specifications

Input: 11-15 VDC (car cigarette lighter or accumulator directly)

Output: 230 VAC +/10% at 50 Hz (+/-3Hz), modified sine wave

Power output: 300 W continuous power (peak power 600 W) USB power output: 5 V / 2.1 A Recommended operating temperature: max +65 °C Material: aluminium Cable: 0.6 m (power x 2,5 sq.mm), 0.6 m (cigarette lighter cable, 1.5 sq.mm)

Dimensions: 180 x 100 x 60 mm Net weight: 740 g

Features

- Single socket 300 W car power inverter
- Allows to connect any AC powered electronics (max. 300 Watt), like notebooks, chargers of mobile phones/cameras, electrical tools etc.
- Overloadand short-circuit protection, plus a built-in cooling fan provide a stable power supply
- LED status indicators and alarm buzzer
- Replaceable fuses

Packaging

Q'ty in crtn, pcs Crtn volume, CUM Crtn weight, kgs Individual package size LxWxH: Carton size LxWxH: Country of origin Barcode Customs code

Package contents

Car power inverter Cigarette lighter cable Crocodile clamp cable User manual 10 0.03159 11.84 210x155x70 mm 450x390x180 mm CN 8716309101226 8504408590

System requirements

Safety precautions:

A car cigarette lighter normally provides power up to 240 W. If your electrical equipment consumes more than 150 W make sure the cigarette lighter does not get hot, otherwise reconnect the invertor to car's accumulator directly, being careful with the polarity.

Certificates



Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com