

EnerGenie Energy Meter USB

EGM-PWM

THE MAGIC OF METERING

- Perfect for analysing your power consumption
- Save energy, save money and preserve the environment
- Suitable for home and business use



Specifiche

Power consumption max: 1.2 W Input voltage: 220-240 VAC Load max: 10 A USB 1.1 or 2.0 compatible interface Computer measurements: voltage and current measuring (RMS values), true power measuring, real energy consumed during a time period (kWH)

Measurements range: up to 250 VAC, 10 A (RMS), 2500 W, 22 MegaW a year

Measurements accuracy: ± 2% (within 50W-2500W power range) Working conditions: +10...40 °C, below 90% humidity Resistance to short-circuits: 1.5 KV Dimensions: 135 x 92 x 78 mm Net weight: 0.3 Kg

Caratteristiche

- USB Power meter, creates exact insight in your energy consumption (voltage/current/power)
- No permanent computer connection required
- Power Manager software helps calculating the actual energy costs of your equipment
- Software provides basic power consumption readings (home use) and advanced readings (business use)

Confezione

Quantità per cartone, pezzi Volume del cartone, CUM Peso del cartone, Kg Individual package size LxWxH: Carton size LxWxH: Paese di origine Barcode Customs code

20 0.027993 6.5 95x140x78 mm 430x310x210 mm CN 8716309068536 9028309000

Contenuto della Confezion

EGM-PWM Software CD User manual USB cable

Certificazioni



Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com

Requisiti di sistema

A free USB port Windows XP/2000/Vista/Windows 7/8