

## Фільтр живлення з пультом дистанційного бездротового керування, 5 розеток

EG-SP5-U6B-RM

### PURE POWER

- Protect your valuable equipment
- Easy switching with wireless remote control
- Also charges most mobile phones and MP3 players



### Особливості

- 5-ти розеточний фільтр живлення з дистанційним керуванням
- Захищає комп'ютери, офісну та домашню електротехніку від перешкод і сплесків в мережі живлення змінного струму
- Два USB порти дозволяють підзарядку портативної електроніки струмом до 2 ампер
- Розроблено для навантаження до 16 Ампер
- Якісний термостійкий пластик
- Захисні шторки розеток
- Отвори для кріплення на стіну

### Пакування

Кількість в коробці, шт.  
Об'єм коробки, куб. м  
Вага коробки, кг  
Розмір індивідуальної упаковки ДхШхВ:  
Розмір коробки ДхШхВ:  
Країна виробник  
Штрих-код  
Митний-код

10  
0.0366  
9.6  
455x112x58 mm  
480x305x250 mm  
CN  
8716309070966  
8544429090

### Комплектація

Surge protector  
Remote control with a battery (12 VDC, type 27A)

### Специфікація

Maximum total power load: 250 V AC, up to 16 A, 50 Hz

Remote control: up to 10 m

Sockets: German (Schuko) type

Plug: built-in German (Schuko) 16 A, 1.8 m cord

USB ports: 2 pcs, 5 V DC, total current up to 2 A

Surge protection: Up = 1.2 kV for L-N, L-G, N-G; Uoc = 4 kV for L-N, L-G, N-G; Uo = 230 V, Uc = 250 V, Ucs = 1.1 x 230 = 253 V

Standby power: 0.6 W

Cable length: 1.8 m

Dimensions: 421 mm x 61 mm x 44 mm

Net weight: 0.73 kg

### Сертифікати

