

# Remote controlled 5 socket surge protector

EG-SP5-TNCU6B-RM

## **PURE POWER**

- Protect your valuable equipment
- Easy switching with wireless remote control
- Also charges most mobile phones and MP3 players

# 

### **Specifications**

Maximum total power load: 250 V AC, up to 16 A, 50 Hz Remote control: up to 10 m Sockets: German (Schuko) type Plug: built-in German (Schuko) 16 A, 1.8 m cord Protected ports: 2 x network 8 pin interface (IN and OUT), 2 x telephone 6 pin interface (IN and OUT) and 2 x TV COAX interface (IN and OUT)

USB ports: 2 pcs, 5 V DC, total current up to 1000 mA Surge protection: Up = 1.2 kV for L-N, L-G, N-G; Uoc = 4 kV for L-N, L-G, N-G; Uo = 230 V, Uc = 250 V, Ucs = 1.1 x 230 = 253 V

Standby power: 0.6 W Cable length: 1.8 m Dimensions: 421 mm x 61 mm x 44 mm Net weight: 0.78 kg

### **Features**

- Remote controlled 5 socket AC surge protector with TV, telephone and network protection
- Protects computers, other office equipment and home appliances from harmful power surges and spikes
- USB ports allow charging any device with up to 1 A power consumption
- Innovative main power 'touch' switch
- Designed for electrical loads up to 16 A
- High quality flame-retardant plastic case
- Child protection shutters
- Mounting holes

### Packaging

Q'ty in crtn, pcs Crtn volume, CUM Crtn weight, kgs Individual package size LxWxH: Carton size LxWxH: Country of origin Barcode Customs code

10 0.0356965 9.8 5000x100x60 mm 470x310x245 mm CN 8716309070973 8544429090

### Package contents

Surge protector Remote control with a battery (12 VDC, type 27A)

### Certificates



Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com