

## EnerGenie Programmable surge protector

### EG-PMS2

#### YOUR SWITCH IS MY COMMAND

- EG-PMS2 is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



#### Karakteristike

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Timers stays active even when the managing PC is turned off
- Child protected sockets
- Mounting holes

#### Pakovanje i slike

Q'ty in crtn, pcs	10
Crtn volume, CUM	0.04413625
Crtn weight, kgs	12.8
Individual package size LxWxH:	465x145x65 mm
Carton size LxWxH:	425x335x310 mm
Country of origin	CN
Barcode	8716309074155
Customs code	8544429090

#### Package contents

EG-PMS2  
User manual  
USB cable  
CD with Power Manager software for Windows

#### Sertifikati



#### Specifikacije

Input voltage 220 – 230 VAC~ 50 – 60 Hz  
Maximum load current 10A  
Maximum current consumed by the EG-PMS2 from the computer USB port: 350mA  
Maximum quantity of EG-PMS2 connected to one computer at the same time: no restrictions (only restricted by the maximum allowed quantity of the USB devices)  
Plug and Play  
Hardware schedule restrictions:  
Maximum number of independent hardware schedules: 16 pcs  
Time interval between the events: from 1 minute to 180 days  
  
Timer accuracy: not more than 3 seconds error per day  
Working temperature range: from +10 to +40 degrees Celsius  
  
Dimensions: 378 x 98 x 55 mm  
Net weight: not more than 1.3 kg

#### Sistemske zahteve

Computer running Windows 7/8/10/11 is required for using the Power Manager software  
A free USB port