

Фільтр живлення, що програмується

EG-PMS2

YOUR SWITCH IS MY COMMAND

- EG-PMS2 is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



Особливості

- Ручне вмикання і вимикання розеток за допомогою керуючої програми на комп'ютері
- Включення і виключення розеток за розкладом
- Включення і виключення розеток залежно від подій, що відбуваються на комп'ютері (старт / вимикання Windows або інших програм, старт \ стоп друку тощо)
- Можливість запрограмувати і зберегти внутрішній розклад, який виконується незалежно від комп'ютера
- Фільтрація радіочастотного шуму: усуває 99% шумових сигналів у діапазоні частот 100 КГц 1 ГГц
- Розетки із захисними шторками
- Отвори для кріплення на стіну

Пакування

Кількість в коробці, шт.	10
Об'єм коробки, куб. м	0.04413625
Вага коробки, кг	12.8
Розмір індивідуальної упаковки ДхШхВ:	465x145x65 mm
Розмір коробки ДхШхВ:	425x335x310 mm
Країна виробник	CN
Штрих-код	8716309074155
Митний-код	8544429090

Комплектація

EG-PMS2
User manual
USB cable
CD with Power Manager software for Windows

Сертифікати



Специфікація

Input voltage 220 – 230 VAC~ 50 – 60 Hz
Maximum load current 10A
Maximum current consumed by the EG-PMS2 from the computer USB port: 350mA
Maximum quantity of EG-PMS2 connected to one computer at the same time: no restrictions (only restricted by the maximum allowed quantity of the USB devices)
Plug and Play
Hardware schedule restrictions:
Maximum number of independent hardware schedules: 16 pcs
Time interval between the events: from 1 minute to 180 days

Timer accuracy: not more than 3 seconds error per day
Working temperature range: from +10 to +40 degrees Celsius

Dimensions: 378 x 98 x 55 mm
Net weight: not more than 1.3 kg

Системні вимоги

Computer running Windows 7/8/10/11 is required for using the Power Manager software
A free USB port