

## EnerGenie Programmable power strip

EG-PM2

### YOUR SWITCH IS MY COMMAND

- EG-PM2 is a power outlet strip with advanced power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- An advanced standby-killer for computer peripherals



### Funkcijos

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Timers stays active even when the managing PC is turned off
- Child protected sockets
- Mounting holes

### Packaging

Dėžių kiekis, vnt  
Dėžių dydis, CUM  
Dėžių svoris, kg  
Individual package size LxWxH:  
Kilmės šalis  
Kilmės šalis  
Brūkšninis kodas  
Customs code

10  
0.0459885  
12.8  
465x145x65 mm  
430x345x310 mm  
CN  
8716309075565  
8544429090

### Pakuotės turinys

EG-PM2  
User manual  
USB cable  
CD with Power Manager software for Windows

### Techniniai duomenys

Input voltage: up to 250 VAC, 50 – 60 Hz  
Maximum load current: 10 A  
Maximum power consumption: 3.5 W  
Built-in power supply  
Hardware schedule possibilities:  
Maximum number of independent hardware schedules 16  
Time interval between the events – from 1 minute to 180 days  
  
Timer accuracy: not more than 2 seconds error per day  
Working temperature range: 0 40 Celsius degrees  
Dimensions: 378 x 98 x 55 mm  
Net weight: up to 1 Kg

### Sertifikatai

