

## 12 V Car power inverter, 300 W

EG-PWC-032

### PURE POWER

- A 230V power source in your car
- Practical USB port for charging mobile devices



### Features

- Single socket 300 W car power inverter
- Allows to connect any AC powered electronics (max. 300 Watt), like notebooks, chargers of mobile phones/cameras, electrical tools etc.
- Overload and short-circuit protection, plus a built-in cooling fan provide a stable power supply
- LED status indicators and alarm buzzer
- Replaceable fuses

### Packaging

|                                |                |
|--------------------------------|----------------|
| Q'ty in crtn, pcs              | 10             |
| Crtn volume, CUM               | 0.03159        |
| Crtn weight, kgs               | 11.84          |
| Individual package size LxWxH: | 210x155x70 mm  |
| Carton size LxWxH:             | 450x390x180 mm |
| Country of origin              | CN             |
| Barcode                        | 8716309075923  |
| Customs code                   | 8504408590     |

### Package contents

Car power inverter  
Cigarette lighter cable  
Crocodile clamp cable  
User manual

### Specifications

Input: 11-15 VDC (car cigarette lighter or accumulator directly)

Output: 230 VAC  $\pm 10\%$  at 50 Hz ( $\pm 3$ Hz), modified sine wave

Power output: 300 W continuous power (peak power 600 W)

USB power output: 5 V / 1 A

Recommended operating temperature:  $+5\ldots+35\text{ }^{\circ}\text{C}$  (max  $-15\ldots+50\text{ }^{\circ}\text{C}$ )

Material: aluminium and plastic

Cable: 600 mm (power x 2, 5 sq.mm), 0.55 m (cigarette lighter cable, 1.5 sq. mm)

Dimensions: 180 x 100 x 60 mm

Net weight: 760 g

### System requirements

Safety precautions:

A car cigarette lighter normally provides power up to 240 W. If your electrical equipment consumes more than 150 W make sure the cigarette lighter does not get hot, otherwise reconnect the inverter to car's accumulator directly, being careful with the polarity.

### Certificates

