

12 V Car power inverter, 1200 W

EG-PWC-035

PURE POWER

- A 230V power source in your car
- Practical USB port for charging mobile devices



Specifications

Input: 11-15 VDC (accumulator directly) Output: 230 VAC +/10% at 50 Hz (+/-3Hz), modified sine wave

Power output: 1200 W continuous power (peak power 2400 W)

USB power output: 5 V / 1 A Recommended operating temperature: +5...+35 °C (max -15...+50 °C)

Material: aluminium and steel Cable: 480 mm (power x 12 sq.mm), 1.0 m (grounding cable, 0.75 sq.mm)

Dimensions: 237 x 165 x 70 mm Net weight: 1975 g

Features

- Dual socket 1200 W car power inverter
- Allows to connect any AC powered electronics (max. 1200 Watt), like notebooks, HiFi or video equipment, chargers of mobile phones/ cameras, vacuum cleaners, electrical tools etc.
- Overloadand short-circuit protection, plus built-in dual cooling fans provide a stable power supply
- LED status indicators and alarm buzzer
- Replaceable fuses

Packaging

Q'ty in crtn, pcs Crtn volume, CUM Crtn weight, kgs Individual package size LxWxH: Carton size LxWxH: Country of origin Barcode Customs code

Package contents

Car power inverter Ring terminal power cables Crocodile clamp grounding cable

User manual

0.045725 13.33 290x220x115 mm 590x310x250 mm CN 8716309075954 8504408590

5

System requirements

Safety precautions:

A car cigarette lighter normally provides power up to 240 W. Connect the invertor to car's accumulator directly, being careful with the polarity.

Certificates



Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com