12 V Car power inverter, 1200 W

EG-PWC-035

PURE POWER

- A 230V power source in your car
- Practical USB port for charging mobile devices



Specifications

Input: 11-15 VDC (accumulator directly)
Output: 230 VAC +/10% at 50 Hz (+/-3Hz), modified sine wave

Power output: 1200 W continuous power (peak power 2400 W)

USB power output: 5 V / 1 A
Recommended operating temperature: +5...+35 °C (max -15...+50 °C)

Material: aluminium and steel
Cable: 480 mm (power x 12 sq.mm), 1.0 m (grounding cable, 0.75 sq.mm)

Dimensions: 237 x 165 x 70 mm
Net weight: 1975 g

Features

- Dual socket 1200 W car power inverter
- Allows to connect any AC powered electronics (max. 1200 Watt), like notebooks, HiFi or video equipment, chargers of mobile phones/ cameras, vacuum cleaners, electrical tools etc.
- Overloadand short-circuit protection, plus built-in dual cooling fans provide a stable power supply
- LED status indicators and alarm buzzer
- Replaceable fuses

Packaging

Q'ty in crtn, pcs	5
Crtn volume, CUM	0.045725
Crtn weight, kgs	13.33
Individual package size LxWxH:	290x220x115 mm
Carton size LxWxH:	590x310x250 mm
Country of origin	CN
Barcode	8716309075954
Customs code	8504408590

System requirements

Safety precautions:
A car cigarette lighter normally provides power up to 240 W. Connect the invertor to car's accumulator directly, being careful with the polarity.

Package contents

Car power inverter
Ring terminal power cables
Crocodile clamp grounding cable
User manual

Certificates

Copyright © 2009–2024, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588
www.energenie.com | postmaster@energenie.com