

Enchufe WiFi Hogar inteligente

EG-PM1W-001

YOUR SWITCH IS MY COMMAND

- EG-PM1W-001 is an easy to use WiFi Smart Home socket with powerful power management options. It enables you to switch the socket on or off via your home WiFi, Internet, by timer schedule, or by programmable special software events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PM1W-001 via Internet from all over the world. The practical and easy to use PowerMan app allows you to control the socket from your smartphone.
- Stay in control of all your electric appliances
- Simply switch devices on or off with your smart phone or tablet
- Built-in WiFi repeater function –Optimal WiFi coverage ensured



Características

- Enchufe inteligente programable con función de WiFi y repetidor WiFi incorporado
- Encienda o apague los dispositivos conectados a través del ordenador, tableta o smartphone
- Ofrece la posibilidad de programación del temporizador programable
- Vincular la función encendido / apagado del enchufe con ciertos eventos de software o de arranque / apagar de Windows
- Fácil acceso desde cualquier ordenador de su red local (a través de su navegador de Internet)

Embalaje

Cantidad por caja, pcs	20
Volumen caja, M3	0.02634825
Peso caja, kgs	5.1
Medidas cajas individuales LxWxH:	80x95x160 mm
Medidas caja LxWxH	430x285x215 mm
País de origen	CN
Código de barras	8716309076555
codigo de aduanas	8544429090

Contenido de la caja

EG-PM1W-001
User manual and Quick installation guide
CD with Power Manager software for Windows

Certificados



Especificaciones

Interface: Wireless LAN IEEE 802.11 b/g/n protocols up to 300 Mbps

WLAN repeater mode

Input voltage: up to 250 VAC, 50 – 60 Hz

Maximum load current: 16 A

Maximum power consumption: 2.5 W

Hardware schedule possibilities:

Maximum number of independent hardware schedules 45

Time interval between the events – from 1 minute to 180 days

Loop period indays, hours, minutes or seconds (single loop period per socket)

Timer accuracy: not more than 2 seconds error per day

Clock synchronisation with NTP server

Dimensions: 108 mm x 76 mm x 55 mm

Net weight: 0.15 kg

Requisitos del sistema

Local area network with a WLAN switch/router

Any Internet-enabled computer connected to the local area network

Computer running Windows® 2000/XP/Vist/Windows 7/8 is required for using the Power Manager software (use of this software is not compulsory)