

 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p>		 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p>	
 <p>ULTIMATE DEFENCE www.energenie.com</p> <ul style="list-style-type: none"> • Informative LCD display • Provides backup power - prevents data loss • Protects your sensitive and valuable equipment • Compact and reliable - ideal for home and small office use  <p>UPS with USB and LCD display</p> <p>1500 VA</p>	 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>Specifications:</p> <ul style="list-style-type: none"> Type: line interactive Waveform: sine wave (AC mains), modified (square) sine wave (battery) Input: 220 V AC ± 25 %, 50 Hz / 60 Hz ± 10 % Output: 220 V AC ± 10 %, 50 Hz / 60 Hz ± 1 % (220 V AC ± 5 % at inverter mode) Switching time: less than 10 ms Backup time: 8...20 mins (depends on the load) Battery: sealed lead-acid 12 V DC / 8 Ah x 2 pcs Charge time: up to 12 hours Sockets: 1 x C14 input, 3 pcs x C13 output, 2 pcs x german Shuko USB control interface: BF socket Operating conditions: 0 °C – 40 °C, at humidity 20 % – 90 % RH non-condensing Power: 1500 VA (900 W) Charging current: up to 1.2 A Noise: < 45 dB at 1 m distance Dimensions: 400 mm x 125 mm x 220 mm Net weight: 10.8 kg <p>System requirements:</p> <ul style="list-style-type: none"> Software is compatible with Windows® Vista, Windows® 7 and Windows® 2008 server <p>Package contents:</p> <ul style="list-style-type: none"> UPS Power cord USB cable Software CD Spare fuse   <p>EG-UPS-034</p>  <p>8 712 37 113 83 0</p> <p>CE, RoHS, WEEE, Recycle, Made in China</p> <p><small>All brands and signs are registered trademarks of their respective owners.</small></p>	 <p>ULTIMATE DEFENCE www.energenie.com</p> <ul style="list-style-type: none"> • Informative LCD display • Provides backup power - prevents data loss • Protects your sensitive and valuable equipment • Compact and reliable - ideal for home and small office use  <p>UPS with USB and LCD display</p> <p>1500 VA</p>	 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>UPS with USB and LCD display, 1500 VA</p> <ul style="list-style-type: none"> Intermittent 1500 VA power supply for PCs Automatic output voltage regulation (AVR) USB interface LCD status indication Short circuit protection Surge, spike and lightning protection Audible and visual alarms Overcharge and overdischarge protection including practical UPS Management software <p>1500 VA UPS mit LCD</p> <ul style="list-style-type: none"> Automatische Ausgangsspannungsregulierung (AVR) USB-Schnittstelle LCD-Statusanzeige Kurzschlusssicherung Überspannungs- und Spannungsspitzenbesicherung sowie Blitzschutz Hörbare und sichtbare Alarme Absicherung vor Überladung und Tiefentladung <p>Noodstroomvoeding met LCD, 1500 VA</p> <ul style="list-style-type: none"> 1500 VA noodstroomvoeding (UPS) voor o.a. PC's Automatische AC spanningregelaar (AVR) Interfacede overspanningsbeveiliging biedt bescherming tegen kortsluiting en spanningstikken veroorzaakt door bijvoorbeeld blikseminslag Hoortbaar en zichtbaar alarm bij stroomuitval LCD status indicator Interne batterij met bescherming tegen overladen of te veel ontladen Inclusief praktische UPS Management software <p>Источник бесперебойного питания 1500 Вольт-ампер с ЖК-дисплеем и USB-интерфейсом</p> <ul style="list-style-type: none"> Автоматический регулятор выходного напряжения (AVR) USB-интерфейс для управления и индикации ЖК-индикатор статуса Защита от короткого замыкания Защита от выбросов напряжения, помех и молний Звуковое и визуальное оповещение о событиях Защита батареи от перезарядки и глубокого разряда <p>Джерело безперебійного живлення 1500 Вольт-ампер з РК-дисплеєм та USB-інтерфейсом</p> <ul style="list-style-type: none"> Джерело безперебійного живлення 1500 Вольт-ампер Автоматичний регулятор вихідної напруги (AVR) USB-інтерфейс для управління і індикації ЖК-індикатор статусу Захист від короткого замикання Захист від викидів напруги, перешкоди і блискавок Звуковий і візуальний оповіщення про події Захист батареї від перезаряду і глибокого розряду <p>Zasilacz awaryjny UPS 1500 VA z LCD</p> <ul style="list-style-type: none"> Automatyczna regulacja napięcia wyjściowego (AVR) Interfejs USB Wyświetlacz LCD informujący o pracy urządzenia Zabezpieczenie przeciw złączonoci Zabezpieczenie przeciwprzepięciowe Ochrona odgromowa Alarm dźwiękowy i świetlny Ochrona przed przeładunkiem oraz przed całkowitym wyczerpaniem akumulatora
<p>size: 390x180x295 mm</p>  <p>Pantone blue 072C</p>  <p>Pantone 376C</p>  <p>60% black</p>			