



Manual switching power distribution unit

English:  
Manual power distribution unit (PDU),  
8 sockets, 1U, 16A  
8 x German Schuko type sockets  
Sockets with safety shutters  
1U rack mountable

Deutsch:  
19" Stromverteiler mit Schalter (PDU),  
8 Steckplätze, 1U, 16 A  
8-fach Stromverteiler mit Schuko-Steckplätzen und Schalter  
Geerdete Anschlüsse mit Safety Shutter  
Passend zur Montage in 19" Racks (1U)

Ukrainська:  
Розгалужувач живлення в стійку 19" 1U,  
8 евро-розеток  
8 вихідних евро-розеток  
Шторки безпеки  
Розмір 1U в 19-ти дюймову стійку

Русский:  
Разветвитель питания в стойку 19" 1U,  
8 евро-розеток  
8 выходных евро-розеток  
Шторки безопасности  
Размер 1U в 19-ти дюймовую стойку

Made in China

www.energenie.com  
PURE POWER  
EG-PDU-012  
8-7163091082495

Nederlands:  
19" stekkerdoos met schakelaar (PDU),  
8-voudig, 1U, 16 A  
8-voudige professionele stekkerdoos met geaarde stopcontacten met beveiligde sluiting  
Eenvoudig te monteren in 19" rack (1U)

Français:  
Adaptateur Multi prises PRO,  
8 prises, 1U, 16 A  
8 x Prises type Schuko  
Avec système de sécurité  
Convient au rack type 1U et autres ...

System requirements:  
Output: 8 pcs, german Schuko type, female  
Input: 1 pcs, german Schuko type, male, 2 m power cord (3 x 1.5 mm²)  
Max. output current: 16 A  
Max. working voltage: 250 V AC  
Output power: up to 3680 W  
Frequency: 50 Hz  
Shell: aluminium

Specifications:  
Temperature: 0 °C ~ 45 °C  
Humidity: 0% ~ 90%  
Dimensions: 432 mm x 44 mm x 44 mm  
Net weight: 0.8 kg

Note: indoor use only

Manual switching power distribution unit



# Manual switching power distribution unit



# Manual switching power distribution unit

- Professional aluminium power supply unit
- Rack mountable - ideal for server cabinets

# Manual switching power distribution unit

size: 550x95x55 mm