




|   |  |  |   |
|---|--|--|---|
|  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with<br/>USB and LCD display</b></p>  |  |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with<br/>USB and LCD display</b></p>   |   |
|  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS<br/>with USB<br/>and LCD display</b></p> <p><b>850 VA</b></p> <ul style="list-style-type: none"> <li>• Informative LCD display</li> <li>• Provides backup power - prevents data loss</li> <li>• Protects your sensitive and valuable equipment</li> <li>• Compact and reliable - ideal for home and small office use</li> </ul>  |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with USB and LCD display</b></p> <p><b>850 VA</b></p> <p><b>Specifications:</b></p> <ul style="list-style-type: none"> <li>→ Type: line interactive</li> <li>→ Waveform: sine wave (AC main), modified (square) sine wave (battery)</li> <li>→ Input: 220V AC ± 25%, 50 Hz / 60 Hz ± 10%</li> <li>→ Output: 220V AC ± 10%, 50 Hz / 60 Hz ± 1% (220V AC ± 5% at inverter model)</li> <li>→ Switching time: less than 10 ms</li> <li>→ Backup time: 8 - 20 mins (depends on the load)</li> <li>→ Battery: sealed lead acid 12 V DC / 8 Ah</li> <li>→ Charge time: up to 12 hours</li> <li>→ Output sockets: 2 pcs x C13, 1 pcs x german Shuko</li> <li>→ USB control interface: RS-485</li> <li>→ Operating conditions: 0°C - 40°C, at humidity 20% - 90% RH non-condensing</li> <li>→ Power: 850 VA (510 W)</li> <li>→ Charging current: up to 1.2 A</li> <li>→ Noise: &lt; 45 dB at 1 m distance</li> <li>→ Dimensions: 340 mm x 95 mm x 165 mm</li> <li>→ Product weight: 7 kg</li> </ul> <p><b>System requirements:</b></p> <ul style="list-style-type: none"> <li>→ Software is compatible with Windows® Vista, Windows® 7/8, Windows® 2008 server</li> </ul> <p><b>Package contents:</b></p> <ul style="list-style-type: none"> <li>→ UPS</li> <li>→ Power cord</li> <li>→ USB cable</li> <li>→ Software CD</li> <li>→ Spare fuse</li> </ul>  <p>EG-UPS-002</p>   <p>CE ENEC In China</p> |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS<br/>with USB<br/>and LCD display</b></p> <p><b>850 VA</b></p> <ul style="list-style-type: none"> <li>• Informative LCD display</li> <li>• Provides backup power - prevents data loss</li> <li>• Protects your sensitive and valuable equipment</li> <li>• Compact and reliable - ideal for home and small office use</li> </ul>  |  <p>ULTIMATE DEFENCE<br/>www.energenie.com</p> <p><b>UPS with USB and LCD display</b></p> <p><b>850 VA</b></p> <p><b>850 VA UPS with USB and LCD display, 850 VA</b></p> <ul style="list-style-type: none"> <li>→ Unterbrechungsfreie 850 VA power supply for PCs</li> <li>→ Automatic output voltage regulation (AVR)</li> <li>→ USB interface</li> <li>→ LCD status indication</li> <li>→ Short circuit protection</li> <li>→ Surge, spike and lightning protection</li> <li>→ Audible and visual alarms</li> <li>→ Overcharge and overdischarge protection</li> <li>→ Including practical UPS Management software</li> </ul> <p><b>850 VA UPS mit LCD, Zukunftsbereit</b></p> <ul style="list-style-type: none"> <li>→ Automatische Ausgangsspannungsregulierung (AVR)</li> <li>→ USB-Schnittstelle</li> <li>→ LCD-Statusanzeige</li> <li>→ Kurzschlusssicherung</li> <li>→ Überspannungs- und Sperrspannungssicherung sowie Blitzschutz</li> <li>→ Hörbare und sichtbare Alarme</li> <li>→ Absicherung vor Überladung und Tiefentladung</li> </ul> <p><b>Источник бесперебойного питания 850 Вольт-ампер с ЖК-дисплеем и USB-интерфейсом</b></p> <ul style="list-style-type: none"> <li>→ Автоматический регулятор выходного напряжения (AVR)</li> <li>→ USB-интерфейс для управления и индикации</li> <li>→ ЖК-индикатор статуса</li> <li>→ Защита от короткого замыкания, скачков и перенапряжения</li> <li>→ Звуковые и визуальные оповещения о сбоях</li> <li>→ Защита батарей от перезарядки и глубокого разряда</li> </ul> <p><b>Джерело безперебійного живлення 850 Вольт-ампер з ЖК-дисплеєм та USB-інтерфейсом</b></p> <ul style="list-style-type: none"> <li>→ Автоматичне регулювання вихідного напруги (AVR)</li> <li>→ USB-інтерфейс для управління і індикації</li> <li>→ ЖК-індикатор статусу</li> <li>→ Захист від короткого замикання, перепаду напруги, перенапруги і блискавки</li> <li>→ Звукові і візуальні оповіщення про події</li> <li>→ Захист батарей від перезарядки і глибокого розряду</li> </ul> <p><b>UPS με οθόνη LCD και USB, 850 VA, μελλοντικό</b></p> <ul style="list-style-type: none"> <li>→ Αυτόματη ρύθμιση εξόδου τάσης (AVR)</li> <li>→ Διασύνδεση USB</li> <li>→ Οθόνη κατάστασης LCD</li> <li>→ Προστασία από βραχυκύκλωμα</li> <li>→ Προστασία από υπερτάση, αυξημένη τάση, κεραυνό και αστραπή</li> <li>→ Με ειδικούς και οπτικούς παύση/ακούσιους</li> <li>→ Προστασία μπαταρίας από υπερφόρτιση</li> <li>→ Διατήρηση/αποφόρτιση πρακτικό λογισμικό</li> <li>→ Περιλαμβάνει προγράμματα λογισμικού</li> </ul> |
|   |  |  |   |

size: 375x145x230 mm

-  Pantone blue 072C
-  Pantone 376C
-  60% black