

 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p>		 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p>	
 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>850 VA</p> <ul style="list-style-type: none"> • Informative LCD display • Provides backup power - prevents data loss • Protects your sensitive and valuable equipment • Compact and reliable - ideal for home and small office use 	 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>850 VA</p> <p>Specifications:</p> <ul style="list-style-type: none"> → Type: line interactive → Waveform: sine wave (AC main), modified (square) sine wave (battery) → Input: 220V AC ± 25%, 50 Hz / 60 Hz ± 10% → Output: 220V AC ± 10%, 50 Hz / 60 Hz ± 1% (220V AC ± 5% at inverter model) → Switching time: less than 10 ms → Backup time: 8...20 mins (depends on the load) → Battery: sealed lead acid 12 V DC / 8 Ah → Charge time: up to 12 hours → Output sockets: 2 pcs x C13, 1 pcs x german Shuko → USB control interface: RS-485 → Operating conditions: 0°C - 40°C, at humidity 20% - 90% RH non-condensing → Power: 850 VA (510 W) → Charging current: up to 1.2 A → Noise: < 45 dB at 1 m distance → Dimensions: 340 mm x 95 mm x 165 mm → Product weight: 7 kg <p>System requirements:</p> <ul style="list-style-type: none"> → Software is compatible with Windows® Vista, Windows® 7/8, Windows® 2008 server <p>Package contents:</p> <ul style="list-style-type: none"> → UPS → Power cord → USB cable → Software CD → Spare fuse  <p>EG-UPS-002</p> <p>6 716399 000042</p> <p>CE ENEC In China</p>	 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>850 VA</p> <ul style="list-style-type: none"> • Informative LCD display • Provides backup power - prevents data loss • Protects your sensitive and valuable equipment • Compact and reliable - ideal for home and small office use 	 <p>ULTIMATE DEFENCE www.energenie.com</p> <p>UPS with USB and LCD display</p> <p>850 VA</p> <p>850 VA UPS with USB and LCD display:</p> <ul style="list-style-type: none"> → Unterbrechungsfreie 850 VA power supply for PCs → Automatic output voltage regulation (AVR) → USB interface → LCD status indication → Short circuit protection → Surge, spike and lightning protection → Audible and visual alarms → Overcharge and overdischarge protection → Including practical UPS Management software <p>850 VA UPS mit LCD-Zukunftsversion:</p> <ul style="list-style-type: none"> → Automatische Ausgangsspannungsregulierung (AVR) → USB-Schnittstelle → LCD-Statusanzeige → Kurzschlusssicherung → Überspannungs- und Sperrspannungssicherung sowie Blitzschutz → Hörbare und sichtbare Alarme → Absicherung vor Überladung und Tiefentladung <p>Источник бесперебойного питания 850 Вольт-ампер с ЖК-дисплеем и USB-интерфейсом:</p> <ul style="list-style-type: none"> → Автоматический регулятор выходного напряжения (AVR) → USB-интерфейс для управления и индикации → ЖК-индикатор статуса → Защита от короткого замыкания → Защита от выброса напряжения, помех и скачков → Звуковые и визуальные оповещения о сбоях → Защита батареи от перезарядки и глубокого разряда <p>Джерело безперебійного живлення 850 Вольт-ампер з ЖК-дисплеєм та USB-інтерфейсом:</p> <ul style="list-style-type: none"> → Автоматичне регулювання вихідного напруги (AVR) → USB-інтерфейс для управління і індикації → ЖК-індикатор статусу → Захист від короткого замикання → Захист від викиртку напруги, пошкодження і скачків → Звукові і візуальні оповіщення про помилки → Захист батареї від перезарядки і глибокого розряду <p>UPS με οθόνη LCD και USB, 850 VA, μελέτη:</p> <ul style="list-style-type: none"> → Αυτόματη ρύθμιση εξόδου τάσης (AVR) → Διασύνδεση USB → Οθόνη κατάστασης LCD → Προστασία από βραχυκύκλωση → Προστασία από απότομες αυξομειώσεις τάσης → Με ειδικούς και οπτικούς πομπικούς ήχους → Προστασία μπαταρίας από υπερφόρτιση → Διατήρηση μπαταρίας πρακτική λειτουργία

size: 375x145x230 mm



Pantone blue 072C



Pantone 376C



60% black